

Part No. WFIL-H1000-18000F

1-18GHz Highpass Filter/SMA



Features:

- Low VSWR
- Low Insertion Loss
- High Performance



Electrical Specification

Pass Band Frequency	1-18GHz
Description	Highpass Filter
Insertion Loss	3.0dB(Max.)
Return Loss	9.5dB min.
Rejection	DC-800MHz : 60dB min
Impedance	50 Ohm
Power Handling	10W
Connector Type	SMA

Environmental Specification

Operating Temperature	-20~+60°C
-----------------------	-----------

Test Curve

