

## Part No. WFIL-H26500-40000F

### 26.5-40GHz Highpass Filter/2.9mm

#### Features:

- Low VSWR
- Low Insertion Loss
- High Performance



#### Electrical Specification

Pass Band Frequency	26.5-40GHz
Description	Highpass Filter
Insertion Loss	1.0dB max.
Return Loss	9.5dB min.
Attenuation	DC-18000MHz: 40dB min
Impedance	50 Ohm
Power Handling	1W
Connector Type	2.9mm
Approx. Size	39x20x10mm

#### Environmental Specification

Operating Temperature	0~+55°C
-----------------------	---------

#### Test Report

