

Part No. WFIL-H6750-18000F

6.75-18GHz Highpass Filter/SMA



Features:

- Low VSWR
- Low Insertion Loss
- High Performance



Electrical Specification

Pass Band Frequency	6.75-18GHz
Description	Highpass Filter
Insertion Loss	1.4dB max.
Return Loss	12dB min.
Rejection	DC-5873MHz:40dB min.
Power	5W
Impedance	50 Ohm
Connector Type	SMA

Environmental Specification

Operating Temperature	0~+55°C
-----------------------	---------

Test Curve

