

Part No. WFIL-N1710-1785F-05

1710-1785MHz Notch Filter/SMA



Features:

- Low VSWR
- Low Insertion Loss
- High Performance



Electrical Specification

Description	Notch Filter
F0	1747.5MHz
Notch Depth	55dB min: 1710-1785MHz
Passband	DC-1660MHz , 1835-8000MHz
Insertion Loss	2.0dB max .
Return Loss	10dB min.
Impedance	50 Ohm
Power Handling	30W
Connector Type	SMA

Environmental Specification

Operating Temperature	0~+55°C
-----------------------	---------

Outline

Unit:mm



Test Report

