

Part No. WFIL-N3600-3800F

3600-3800MHz Notch Filter/ SMA

Features:

- Low VSWR
- Low Insertion Loss
- High Performance



Electrical Specification	
Description	Notch Filter
F0	3700MHz
Notch Depth	50dB min: 3600-3800MHz
Passband	DC-3400MHz , 3900-7000MHz
Insertion Loss	2.5dB max
Return Loss	10dB min: DC-3400,3900-5000MHz 5dB:5000-7000MHz
Power Handling	20W
Impedance	50 Ohm
Connector Type	SMA
Approx. Size	170x30x43 mm

Environmental Specification	
Operating Temperature	0~+55°C